

# SC-MIXAMPE50-Loop

## 3 Channel Audio Amplifier



- 3 Channel Input
- Stereo 2 x 50 Watt 8 ohm Amplifier
- Audio Loop Output
- LED Indicator Panels

It designed stereo, optical, analog 2x50W amplifier and audio mixer. Available to mix analog and digital inputs and it direct 2x50 Watt 8 or 1x100Watt 4 Ohm output.

SC-MIXAMPE50-Loop easy to manage over network with web-based user interface. It has Telnet AP to be used with 3. party products , additionally it allows you to use with the buttons on the front panel such as volume etc.

### Features

- It has optical audio input
- It has 3 channel (Optik, L+R stereo and Analog) input
- Easy audio setting with rotate knob,
- Output power maximum 2x50 Watt /8 ohm
- Audio loop output,
- Amplifier output can select stereo or mono
- It can control with WebGUI, TCP/IP, front panel button and RS232



**Input and Output**

Inputs	1x L+R , 1x Optical and 1x Analog
Outputs	1x 3.5mm Stereo, 1x4-pin 5.08mm (Stereo/Mono) and 1x Loop
Output Features	1x 100W @ 4Ω 2 x 50W @ 8Ω SNR > 80dB @20Hz – 20kHz THD+N @ 1 %@1KHz 50W , 75dB @ 20Hz – 20kHz

**Network Feature**

Ethernet	IP
IP Address Feature	DHCP, Fixed IP

**Management Features**

Hardware Software Upgrade	USB port
Management Options	WebGUI, TCP/IP , RS232 , front panel buttons

**General Features**

Power Connection	36V DC 2.66Amp
Working Temperature	-10°C~55°C
Humidity Range	10~90% RH
Storage Temperature	-25°C~70°C
ESD Protection	±8kV (air gab discharge) ±4kV (connection discharge)
Dimensions	148mm × 165mm × 44mm - Width/Depth/Height
Weight	720g
Power Value	1.48W
Mounting	Desktop

**Certifications**

EU/USA	CE
--------	----

**Package Details**

Dimensions (packaged)	149mm×166mm×45mm- Width/Depth/Height
Weight (packaged)	730g
Package Content	1x SC-MIXAMPE50-Loop , 36V/2.66A DC Power Adaptor and Power Cable, 1x User Manual



Front View



Rear View